

BizFAX- Business Standalone FAX Server

BizFAX Client is a virtual fax extension that works with BizFAX Server. Not only receive fax automatically and save it as electronic file, but also make outbound call manually and automatically to send a fax.

BizFAX contains a BizFAX Printer module and a BizFAX Editor module. BizFAX Printer can easily convert documents as doc, xls or pdf to tiff format; BizFAX Editor helps user to dramatically improve the efficiency in doing office works like make annotations, signature and stamp on a document.

BizFAX family consist of 2 models that are E100, E200. BizFAX can easily meet the unique requirements of different sizes of companies.

According to the survey of existing BizFAX Standalone Fax Server users, and compared with the traditional fax-machine, it can save 98% of the paper consumed by faxes. No need to worry about the invasion of useless advertisements. It is a one-time but affordable investment which helps realizing the relaxed, convenient, clean and efficient official working environment from then on.



| No. | Identifying |
|-----|---|
| 1 | Green Light: Indicates the power connection is normal. |
| 2 | Green Light blink: Indicates the server system is in working. |
| 3 | Green Light: Indicates the system is ready. |
| 4 | Green Light blink: Indicates the internet interface in use |
| 5 | Green Light: Indicates the PSTN lines connect successfully. |
| 6 | Green Light blink: Indicates the PSTN line in use. |
| 7 | Green Light: Indicates the port is work well. |
| 8 | Green Light blink: Indicates the FAX machine in use. |



2) Back Side



| No. | Identifying |
|-----|---|
| 1 | Eth: To connect to the LAN |
| 2 | Line: To Connect to the Fax Line |
| 3 | Phone: If you have an analog fax machine, connect it to the port. |
| | You can also send and receive fax by the analog fax |
| | machine. It could be used as a scan machine and a printer. |
| 4 | Reset: Press it to restore to factory setting |
| (5) | Power: Connect the power adapter to this port. |

| Model | FAX Line(FXO Ports) | Users (default) | Weight |
|-------------|---------------------|-----------------|---------------|
| BizFAX E100 | 1 | 25 | 0.5kg (Gross) |
| BizFAX E200 | 2 | 50 | 0.5kg (Gross) |

Basic Specifications

| Size | 193*153*30 mm | Client Software OS | Win 2000/XP/Vista/7 |
|--------------------|--|--------------------|---|
| Fax Rate | 14.4k~2.4k | LAN protocol | TCP/IP |
| Code compress mode | MH/MR/MMR | Fax Agreement | ITU-T G3 T.4 |
| Caller ID | Support FSK / DTMF | Storage Capacity | About 15000 pages |
| Server support | WEB UI/Client Software | Language | Chinese Traditional/ Chinese Simplified/ English/Hebrew/ Portuguese |
| Power | Input: 100-240V 0.5-1A 50/60HZ Output: 12V 1A | Maximum Power | 12 W |



| Running Environment | +10∼35°C | Humidity | 20~80% rh |
|------------------------------------|-------------------|-------------------------------------|-----------------|
| Network | 10M/100M Ethernet | Remote Service | Support |
| Fax Line Interface | RJ-11 | Network Interface | RJ-45 |
| Client Software Upgrade | Free | Import OutLook Contacts | Support |
| Fallback when power down | Support | Receive fax even shun down computer | Support |
| Fax Resolution | 200/200 DPI | Fax Encryption | Support |
| Fax to E-Mail | Support | Auto Receive Fax | Support |
| Auto Send Fax | Support | Auto dispatch Fax | Support |
| Group Send Function | Support | Internal Transfer Fax | Support |
| Resend Failed Faxes | Support | Send Fax at Certain Time | Support |
| Status Monitor | Support | Fax Reminder | Support |
| Fax Archiving | Support | Fax Revising & Transmitting | Support |
| Link of the fax-machine | Support | Custom Voice Prompts | Support |
| Identity Authentication & Password | Support | View & Edit Fax | Support |
| Print Out Fax | Support | Electronic Seal & Signature | Support |
| BizFAX Server Management | Support | Digits of extension | Customizable |
| User Management | Support | Fax Log Management | Support |
| Fax Queue Management | Support | Contacts Management | Support |
| Memory Capacity for contacts | Unlimited | Fax Monitor | Support |
| Printer Server | Support | Fax Router | DTMF, CID, Port |
| Lightning Proof | Support | Compatible Line | PSTN (FXO) |